

MAP 2100: Alternate Binary Synchronous Communications (Alt BSC) Adapter

Symptom Explanation	Conditions That Could Cause This Symptom
You have entered this MAP because you received a 21XX error code, or you have been directed here from another MAP.	<ul style="list-style-type: none">• The alternate BSC Adapter is failing.• The adapter cable is failing.• Jumpers are incorrectly set.

Ensure the following conditions exist:

1. An adapter is set for primary BSC Adapter operation.
2. A second BSC Adapter is installed and is set for alternate BSC Adapter operation.

001

- Power off the system.
- Insert the Advanced Diagnostics diskette into drive A.
- Power on the system.
- Run the Alternate BSC Adapter tests. Use the **(RUN TESTS ONE TIME)** option.
- Follow the instructions on the screen. Do not power off the system during this test.

Note: Use wrap plug (IBM Part 8529280) when instructed to install the wrap plug.

(Step 001 continues)

001 (continued)

DID YOU RECEIVE AN ERROR MESSAGE?

Yes No

002

You have successfully completed the Advanced Diagnostic tests. If you suspect an intermittent problem, start an error log. If you need instructions, refer to the Reference manual.

003

Replace the FRU indicated on the display.
